

ECP3586T - Performance

Rated Load	0%	25%	50%	75%	100%	125%	150%	S.F.
Power Factor	19.0	50.0	70.0	80.0	85.0	88.0	89.0	87.0
Efficiency	0.0	75.2	83.8	86.2	86.5	86.4	85.5	86.5
Speed (RPM)	3,598	3,571	3,548	3,525	3,501	3,476	3,448	3,486
Line Amps	1.10	1.28	1.65	2.09	2.55	3.08	3.64	2.90